

1940nm Polarization Maintaining Tap Coupler/ Isolator Hybrid Combination

Key Features

- Compact Size
- Low insertion loss
- High channel Isolation
- High Extinction Ratio
- High stability and reliability

Applications

- Fiber laser
- Fiber amplifier
- Fiber Sensor
- Communications
- Laboratory R&D

DK Photonics' Tap Coupler/Isolator Hybrid Combination is a combination of a wavelength division multiplexer, tap coupler and an isolator in a compact package. All input and output fibers are polarization maintaining. This product has an extremely low insertion loss, a very stable tap-coupling ratio, high isolation, and high return loss. This product offers integrated solution to amplifier application by combining more functions into a very compact package.



For more Info

Please contact us at:

Tel: +86-755-23736280

Fax: +86-755-26746512

E-mail: sales@dkphotonics.com

<https://www.dkphotonics.com>

Add.:


4F, Bldg. 18, Qinghu Industrial Park,
 Dahe Road, Longhua Dis.,
 Shenzhen, China 518109

Package Dimension



* If Tap port is on the input side (Backward Tap), Tap is both axis working. If Tap port is on the Output side (Forward Tap), it is fast axis blocked, slow axis working. The default tap is on the input side.

*Due to ongoing design improvements, the package size is subject to change. Please contact DK Photonics for confirmation if you have special requirements.



1940nm Polarization Maintaining Tap Coupler/ Isolator Hybrid Combination

Performance Specifications

Parameter	Unit	Values	
Stage of Isolator	-	Single Stage	Dual Stage
Signal Central Wavelength (λ_c)	nm	1940	
Max. Signal Excess Loss, λ_c , @ 23°C	nm	1.4($\lambda_c \pm 20$ nm)	1.7($\lambda_c \pm 20$ nm)
Min. Signal Isolation, λ_c , @ 23°C(Isolator)	nm	16($\lambda_c \pm 50$ nm)	35($\lambda_c \pm 50$ nm)
Tap Ratio	%	1~50	
Tap Channel Typ. Loss	dB	1%(19.0~21), 2%(16.2 ~ 19.0), 5%(12.2 ~ 15.0)	
Min. Extinction Ratio @ 23°C	dB	Type B: 20, Type F: 22	
Min. Return Loss	dB	50	
Max. Power Handling (CW)	W	0.5, 1, 2, 5, 10	
Max. Peak Power for Pulse	kW	1, 5,10	
Max. Tensile Load	N	5	
Fiber Type	-	SMF-28e, SM1950 or PM1550 or PM1950 fiber for Tap port, PM1550 or PM1950 fiber for Input & output port	
Operating Temperature	°C	-5 to +70	
Storage Temperature	°C	-40 to +85	
Package Dimensions	mm	$\Phi 5.5 \times L35(<5W)$, 60x12x8(>5W)	

- Above specifications are for device without connector.
- For devices with connectors, IL will be 0.3dB higher, RL will be 5dB lower and ER will be 2dB lower. The default connector key is aligned to slow axis. Power transmits through the connector less than 2W.
- Type B: Both axis working, Type F: Fast axis blocked, the default is Type B if without request.
- If there is pulse application, please be sure to inform us of pulse energy and peak power.
- If you have questions about the axial direction, please contact us.

Order information P/N:PMTIH-S/D-①-②-③-④-⑤-⑥-⑦-⑧-⑨ (S: Single Stage, D: Dual Stage)

When you inquire, please provide the correct P/N number according to our ordering information, and attach the appropriate description would be better. If need any connector, we do not recommend choosing a 250 μ m bare fiber pigtail.

①	②	③	④	⑤	⑥	⑦	⑧	⑨
Wavelength	Tap Ratio	Optical Power	Tap Configuration	Axis alignment	Fiber type	Pigtail Diameter	Fiber Length	Connector
1940:1940nm	01:1% Tap 02:2% Tap 05:5% Tap	L: <0.5W 1:1W 3:3W 5:5W 10:10W	F: Forward Tap B: Backward Tap	F: Fast axis blocked, Slow axis working B: Both of axis working	XX: fiber name	25:250 μ m bare fiber 90:900 μ m Loose Fiber XX: Others	08:0.8m 10:1.0m 15:1.5m XX: Others	00: None FP: FC/PC FA: FC/APC XX: Others

Part Number Example: PMTIH-S-1940-01-1-F-P19-90-10-FA

Description: 1940nm Polarization Maintaining Tap Coupler/Isolator Hybrid Combination, Single Stage, , 1% tap, 1W, and Fast axis blocked, Slow axis working, PM1950 fiber, with 0.9mm OD loose tube, 1.0m fiber length, and FC/APC connectors at all ports.

Ordering Information for Custom Parts

If you need to customize other specifications, please provide detailed description for your requirement.