



## 1030nm Band Pass Filter

### Performance Specifications

Parameter	Unit	Specification	
Center Wavelength	nm	1030	
Max. Pass bandwidth@0.5dB	nm	2	6
Max. Stop bandwidth@25dB down	nm	6	10
Max. Insertion Loss of Pass Band	dB	0.8	0.8
Max. PDL	dB	0.10	
Min. Return Loss	dB	50	
Fiber Type	-	1060-XP fiber, or other	
Max. Power Handling	W	0.3, 1, 2, 3, 5, 10	
Max. Tensile Load	N	5	
Operating Temperature	°C	-5 - 75	
Storage Temperature	°C	-40 - 85	
Dimensions	mm	Φ5.5×L35	

\*Above specifications are for device without connector.

\*For devices with connectors, IL will be 0.3dB higher, RL will be 5dB lower, Power transmits through the connector less than 2W.

\*For >10W high power applications, we will use heat sink package, contact DK Photonics for details.

\*Since the function of the BPF is to block unwanted noise signals, the blocked light remains in the interior of the housing, so we do not recommend applying it to too high power or adding reflection port to reflect the blocked light.

\*Other center wavelengths and bandwidths can also be customized, but MOQ is required, please contact us.

### Order information P/N: BPF-①-②-③-④-⑤-⑥-⑦

When you inquire, please provide the correct P/N number according to our ordering information, and attach the appropriate description would be better. If need any connector, we do not recommend choosing a 250μm bare fiber pigtail.

①	②	③	④	⑤	⑥	⑦
Port	Wavelength	Pass bandwidth	Power Handling	Pigtails Diameter	Fiber Length	Connector
101:1x1(default)	30:1030nm	2:2nm	L:<0.3W	25:250μm bare fiber	05:0.5m	00: None
102: 1x2(With reflect unwanted signals port)		6:6nm	1:1W 2:2W	90:900μm Loose Fiber XX: Others	08:0.8m 10:1.0m XX: Others	FP: FC/PC FA: FC/APC LA: LC/APC XX: Others

**Part Number Example:** BPF-101-30-2-L-25-10-00

**Description:** 1030nm Band Pass Filter, 1x1 port, 2nm pass bandwidth, 300mW power, 1.0m 1060-XP fiber, with bare fiber, no connectors at all ports.

### Ordering Information for Custom Parts

If you need to customize other specifications, please provide detailed description for your requirement.